



Update instructions for the update to version 3.5

C-MOR System requirements: V 3.12

Notice:

If you have a C-MOR with a version older than 3.0, then you are not allowed to install this update. The C-MOR will not work any longer after trying to install this update and needs to be sent in to repair it!

Please use the update function of the C-MOR:

Update steps:

1. Make sure your C-MOR has Version 3.12 installed. Update to version 3.12 first if this is not the case
2. Disable all cameras
3. Call the URL <http://<C-MOR-Address>/en/update.pml>:
4. Under servername use "update.c-mor-video.com" and under path: [/updates/v3.50/<c-mor-version>](http://updates/v3.50/<c-mor-version>) (be sure to use c-mor names given below or it will not work.)

Possible c-mor versions are: "c-mor3", "c-mor6", "c-mor9" or "c-mor15"

Important: C-MOR must not reboot at this time as requested after installing the updates

5. Install the updates
6. After the update call the URL <http://<C-MOR-Address>/createjava.pml>
7. Also call in a second step the URL <http://<C-MOR-Address>/update-config-files-java.pml>
8. Reboot your C-MOR now
9. Now set the access permissions in the system administration in "User cam rights" for each user. Remove all rights, save, and add the rights as before again and save.
10. Activate all cameras and check under the camera settings menu if you need to configure the new PTZ configuration. This completes the upgrade process. Please verify if the Java-Player runs correctly and show a fluent camera live view.